



PHD-8VX

RS232 Command List

Com Port Communication:

Baud rate: 115200, Data: 8 bit, Parity: none, Stop: 1 bit, Flow control: none.

Remote Control Keys:	Character typing on PC (case sensitive)
[KEY_POWER]	power
[KEY_TV]	tv
[KEY_PHOTO]	photo
[KEY_MUSIC]	music
[KEY_PICTURE]	pic
[KEY_ASPECT]	v
[KEY_INPUT]	in
[KEY_CLEAR]	c
[KEY_GOTO]	last
[KEY_LEFT]	l
[KEY_RIGHT]	r
[KEY_UP]	u
[KEY_DOWN]	d
[KEY_VOLUME_UP]	vu
[KEY_VOLUME_DOWN]	vd
[KEY_MUTE]	mute
[KEY_CHANNEL_UP]	cu
[KEY_CHANNEL_DOWN]	cd
[KEY_AUDIO]	a
[KEY_CAPTION]	cc
[KEY_SLEEP]	sleep
[KEY_DIGIT_0]	0
[KEY_DIGIT_1]	1
[KEY_DIGIT_2]	2
[KEY_DIGIT_3]	3
[KEY_DIGIT_4]	4
[KEY_DIGIT_5]	5
[KEY_DIGIT_6]	6
[KEY_DIGIT_7]	7
[KEY_DIGIT_8]	8
[KEY_DIGIT_9]	9
[KEY_DOT]	.
[KEY_ENTER]	ok
[KEY_GUIDE]	g
[KEY_MENU]	m
[KEY_INFO]	i

Note: i). other key commands are unavailable in this time.

ii). Preliminary testing only. No warrant. Prevent random char. entry crashing system, User Precaution.